

LED ELECTRONIC RIBBON LIGHT DRIVERS



LEDDR-12V-48DP
LEDDR-24V-48DP



LEDDR-12V-WP-60
LEDDR-24V-WP-60



LEDDR-12V-72W
LEDDR-24V-72W



LEDDR-12V-150W
LEDDR-24V-150W



LEDDR-12V-300W
LEDDR-24V-300W



LEDDR-12V-400W
LEDDR-24V-400W



LEDDR-12V-WP-200W
LEDDR-24V-WP-200W

F7

LED ELECTRONIC NON-DIMMABLE DRIVERS

LED ELECTRONIC NON-DIMMABLE DRIVERS

Can be dimmed on the secondary side using electronic dimmers (see page 157)

12-VOLT

CATALOG NO.	MAX WATTAGE	AMP	OPERATING VOLTAGE		15A PLUG & MALE 12V CONNECTOR
			INPUT	OUTPUT	
LEDDR-12V-48DP	48W max	4AMP	120V AC	12V AC	Y
LEDDR-12V-WP-60	60W max	5AMP	120V AC	12V AC	N
LEDDR-12V-72W	72W max	6AMP	120V AC	12V AC	Y
LEDDR-12V-150W	150W max	12.5AMP	120V AC	12V AC	N
LEDDR-12V-300W	300W max	25AMP	120V AC	12V AC	N
LEDDR-12V-400W	400W max	33AMP	120V AC	12V AC	N
LEDDR-12V-WP-200W	200W max	16.66AMP	120V AC	12V AC	N

24-VOLT

CATALOG NO.	MAX WATTAGE	AMP	OPERATING VOLTAGE		15A PLUG & MALE 12V CONNECTOR
			INPUT	OUTPUT	
LEDDR-12V-48DP	48W max	2AMP	120V AC	24V DC	Y
LEDDR-12V-WP-60	60W max	2.5AMP	100V~130VAC	24V DC	N
LEDDR-12V-72W	72W max	3AMP	120V AC	24V DC	Y
LEDDR-12V-150W	150W max	5AMP	120V AC	24V DC	N
LEDDR-12V-300W	200W max	8.33AMP	100V~130VAC	24V DC	N
LEDDR-12V-400W	300W max	12.5AMP	120V AC	24V DC	N
LEDDR-12V-WP-200W	400W max	16.66AMP	120V AC	24V DC	N

